## **Battery Info**

Your Bluetooth keyboard takes 2 AAA batteries. When your keyboard needs to have it's batteries replaced, the red battery light on the left hand corner of the device will blink.

Estimated battery life of 3 months, with 4 contiguous typing hours per day. Note: keyboard will go into sleep mode when not in use, to preserve battery life.

#### Additional battery indicator light information:

States	Behavior
Power on	Green light on for 1 sec
Pairing	Flashing alternating red and green lights for 5 minutes or until paired
Connected	Green light flashes (for .1 seconds) 3 times
Pairing Success	Green light flashes (for .1 seconds) 5 times
Reconnect	Green light flashes (for .5 seconds) 10 times
Low battery	Red light flashes 5 times, every 30 seconds

## Goldtowch Mini Keyboard

III GTA-0033 GOLDTOUCH WIRELESS BLUETOOTH MINI KEYBOARD



# User Manual

## **Device Support**

As mobile devices continue to expand in the marketplace, the Bluetooth Mini Keyboard will endeavor to support all possible devices through compliance with hardware and wireless standards. The Bluetooth Mini Keyboard is compatible with any Bluetooth 3.0 enabled device, including laptops, tablets, and Playstations.

Various devices also provide different pairing processes that should be followed using the steps provided by the device manufacturer.

To obtain support, download guides, and to learn about additional ergonomic and mobile ergonomic products from goldtouch, please visit our website at:

www.goldtouch.com.

Windows XP SP2+ Windows Vista, 7 Windows 8 Windows Mobile Windows Phone

Mac OS X 10.4+ iPad w/ iOS 4.2.1+ iPhone iOS 4.2.1+

#### Google Android 2.3+\*

\* Due to the open source nature of this OS, Goldtouch cannot warrant support for all Android devices. Congratulations on your purchase of a Goldtouch Mini Keyboard.

Thank you for joining the evolution in ergonomic mobile computing.

The Goldtouch Bluetooth Mobile Mini Keyboard provides you the convenience of a lightweight and stylish wireless keyboard, anywhere you go, no matter what mobile device you use. The Bluetooth Mini Keyboard is great for quick typing tasks that don't require a full sized keyboard, but allows users to avoid awkward touch screen typing or typing on tiny mobile device keypads.

Excellent Bluetooth Wireless Technology allows the keyboard to connect to PC's, Mac OS, Laptops, Tablets, iPhone's, iPad's and Playstations.

Let's face it, the mobile user relies more and more on portable devices with touchscreen keyboards or tiny keys, but these are simply not practical for performing lengthy and complex typing tasks.

We thank you for your purchase and wish you years of personal comfort and productivity.

© 2013 Keyovation, LLC. All rights reserved. Goldtouch, the Goldtouch logo and Productivity through Prevention<sup>®</sup> are registered trademarks of Key Ovation, LLC







## III How to pair your Bluetooth Go! with your device

#### **Bluetooth Pairing with PC**

- Turn on the power using the power switch on the back of the keyboard. The Green Battery light will briefly turn on.
- 2. Press the **Connect** button on the back of the Keyboard. When the keyboard is in pairing mode, the battery light will blink red and green.
- 3. Scan for Bluetooth devices on your PC or tablet.
- 4. Once your PC has recognized the device, you will be presented with a pairing code. Enter the pairing code on the Bluetooth keyboard and press Enter. Once the keyboard is connected, the green light will flash three times.

#### **Bluetooth Pairing with MAC**

- 1. Turn on the power using the power switch on the back of the keyboard. The Green Battery light will briefly turn on.
- 2. Press the Connect button on the back of the keyboard. When the keyboard is in pairing mode, the battery light will blink red and green.
- 3. Scan for Bluetooth devices on your Mac, iPad or iPhone.
- 4. Once your Mac has recognized the device, you will be presented with a Passkey. Enter the Passkey on the Bluetooth keyboard and press Enter. Once the keyboard is connected, the green battery light will flash three times.

#### **Bluetooth Pairing with Android**

- 1. Turn on the power using the power switch on the back of the keyboard. The Green Battery light will briefly turn on.
- 2. Press the Connect button on the back of the keyboard. When the keyboard is in pairing mode, the battery light will blink red and green.
- 3. Scan for Bluetooth devices on your Android device.
- 4. Once your Android device has recognized the keyboard, you will first be asked to enter in a Pin Code for your keyboard on your Android Device. Please note, you may enter any 4 digit Pin number that you like.
- 5. Next, enter the same 4 digit Pin Code (from step 4) on your Goldtouch Keyboard and press Enter. (We recommend that you write down your Pairing code, or you will need to re-pair if your device disconnects.)

#### **Additional Bluetooth Pairing Instructions**

The Goldtouch Bluetooth Mini Keyboard is Bluetooth 3.0 enabled and is compatible with all of your Mac and PC devices, including your desktop, notebook, tablet, smart phone, Apple TV, Roku, Playstation, Xbox, PS3, or other smart Bluetooth enabled devices. To pair additional Bluetooth enabled devices like the Samsung Galaxy and Playstation, please follow the PC pairing directions above.

Once your Bluetooth Mini Keyboard has been paired to your device, it will maintain its connection (even when you power down your devices). When you power on your Bluetooth device and Mini Keyboard, the keyboard will briefly go through a Reconnect process (the green battery indicator light will flash for .5 seconds, 10 times during this process). Once you're reconnected, you can begin working.



Apple



Android



## **III FN- Function Features**

To activate the FN (Function) features on your Goldtouch Bluetooth keyboard, press and hold the FN key and select the following:

	Play/Pause
<b>◄</b>	Rewind
	Fast Forward
$\Join$	Mute
¢	Volume Down
⊲≫	Volume Up

## III FN - Embedded Numeric Keypad Feature

To activate the Bluetooth keyboards embedded numeric keypad:

- 1. Hold down the FN key, and press Num Lk.
- 2. Continue Holding the **FN** key and press the corresponding numbers/symbols for the embedded numeric keypad.
- 3. When finished, release the **FN** key and continue typing.
- 4. Once you have engaged the Num Lock feature in step 1, simply press and hold the FN key to type numbers on the embedded numeric keypad.

To Turn off Num Lock, hold down the FN key and press Num Lk.

### III Key Layout

